



End Outlet Bridged 2 connectors: FM/TV-SAT

End outlet bridged equipped with two IEC connectors (male on the left, female on the right) with TV+SAT outputs.

It is bridged and therefore the full FM, TV and SAT input signal is available on both connectors.

Equipped with signal pass-through, which allows the series connection of multiple outlets.

Ref.	5270
EAN13	8424450052709

Other features

Complement	Outlet
-------------------	--------

Packaging info

Box	1 pcs.
Carton	10 pcs.
Pallet	3600 pcs.

Physical data

Net weight	100.00 g
Gross weight	100.00 g
Width	70.00 mm
Height	70.00 mm
Depth	27.00 mm
Main product weight	89.00 g

Highlights

- High shielding
- Robot-controlled automated manufacturing

Main features

- Made of Zamak, high strength
- Compatible with coaxial cable with sheath diameters in the 5-to-6,9 mm range (Ø 5...6,9 mm)

Discover

Televes outlets: Screw-free mounting

A class A outlet offering numerous advantages:

- The inner conductor is connected simply by pushing, without the need for screws; still the gripping force is equivalent
- Supports inner conductor diameters from 0.65 mm to 1.2 mm, and external cable diameters from 5 mm to 6.9 mm
- F-connector type conic guide for easy inner conductor introduction
- Wide margin in inner conductor length (from 5 mm to 15 mm), which makes short circuits between core and mesh difficult
- Tilt-up, self-supporting, full-opening clamp
- The clamp is equipped with 3 jagged rows in 9 mm for a perfect braid fixing
- Printed circuit board perforation to make the faceplate fixing screw compatible
- Rounded edges to prevent cuts
- Class A shielding

Furthermore, this product range includes several engravings on the chassis:

- CE marking
- Numerical and logical references
- Input and output indications
- Cable stripping dimensions

Technical specifications : Ref. 5270

Fastening method			Without screws	
Number of connectors			2	
R/TV Connector			"IEC" male	
SAT Connector			"IEC" female	
Pass-through output			Yes	
Bands				
Frequency range	MHz	TV		SAT
		5 ... 862		950 ... 2400
Through losses	dB	1		1
Attenuation: R/TV Connector	dB	1		--
Attenuation: SAT Connector	dB	--		1
DC pass			SAT□In / Out□In	
Max. current	mA		350	