



Terrestrial and satellite signal mini-combiner 2 inputs: MATV-SAT

2-input mini-combiner that combines a terrestrial signal with a satellite signal into a single output. Its innovative ultra-small size allows installation virtually anywhere, including small pattrass boxes. Furthermore, miniaturization applies also to the electronics, which improve electrical behaviour and reduce impulsive noise.

Ref.	745220
Logical ref.	ESW11
EAN13	8424450186268

Packaging info

Box	10 pcs.
-----	---------

Physical data

Net weight	56.00 g
Gross weight	56.00 g
Width	57.00 mm
Height	45.00 mm
Depth	12.00 mm

Highlights

- EasyF connection system: easy to install, savings on mounting
- High-screening Zamak chassis
- Current pass from the output to the SAT input, for LNB supply

- Outstanding reliability: automated manufacturing using new generation micro-components
- Indoor or outdoor installation (with ref. 417801 case)

Discover

EasyF connection system: simplicity and savings

EasyF is an innovative connection concept where the inner conductor of the coaxial cable is directly inserted in the device, thus improving connection reliability. Thanks to the absence of F connectors, the chassis can be reduced and the connection of two cables secured with a single screw.

- Real time savings: speeding the installation is possible without the need for coaxial cable termination. Furthermore, there is no need for screwing the connectors on the device, which is sometimes difficult when there is little room
- Connection reliability: the clamp holding the cables prevents the coaxial cable to come off
- Cost savings: no additional connectors are required (neither F nor IEC)
- Space optimization: inputs and outputs are always on the same side of the device to prevent coaxial cables from bending, and to make working inside cabinets and register boxes easier
- Very easy three-step mounting: only screwing and unscrewing the covers is required to connect both cables:

1. Unscrew the device's cover to access the connection
2. Insert the previously stripped coaxial cables
3. Close the cover and screw to ensure connection

Learn more about EasyF system reliability

With EasyF, the connection between the coaxial cable and the device is carried out using an automated system for contact insertion of the inner conductor, without any soldering.

- Always as new: the device's operating life increases when the factor of solder wearing out with time is removed
- Failure rate reduction: usually produced as a result of cold soldering joints

- Electromagnetic behaviour optimization: for high frequencies
- Our commitment with environment is reinforced: pollution caused by the welding process is eliminated and production power consumption is reduced

Technical specifications : Ref. 745220

Connectors			"F" type	
Number of inputs			2	
Number of outputs			1	
Frequency range	MHz	47 ... 790		950 ... 2400
IN (TERR) -> OUT attenuation	dB	1.5		> 30
IN (SAT) -> OUT attenuation	dB	> 35		1.5
Return losses (typ.)	dB	> 10		> 10
Operating temperature	°C		-5 ... 45	
Protection index (IP)			23	