



Televés reserves the right to modify the product

F 4W terminal tap 5...2400MHz 8dB

4-way tap with F connectors, for SMATV signals. Its tap losses (8dB) as well as the lack of pass output, make it suitable for installation in floor 1.

It presents a high efficient electrical behavior thanks to the miniaturization applied in the electronic components included. In addition, its Zamak chassis provides great shielding.

It is conceived for indoor installation, for wall, rack plate or standard DIN rail assembly. Supplied in 10-unit boxes.

Ref.	519341
Logical ref.	AZS48FZ
EAN13	8424450267882

Packaging info

Box	10 pcs.
------------	---------

Physical data

Net weight	82.00 g
Gross weight	82.00 g
Width	109.00 mm
Height	54.00 mm
Depth	18.00 mm

Highlights

- Assembly flexibility: it can be installed screwed to the wall, on rack plates with nuts on their

connectors, or on a standard DIN rail (with adapter ref. 519901)

- Comfortable screwing of the cable, thanks to a 10° inclination angle of the F-connectors from the installation wall
- Space optimization in registers and cabinets: their inputs/outputs are always located on the same side
- Better organization of the installation: allows cabling passage through its rear part
- F-Series elements can be chained between them with the ground screw, requiring in this case a single grounding cable
- Signal level is maintained in outlets, even with long cable deployment, thanks to a better flatness response
- Outstanding reliability: robotized manufacturing using new generation micro-components
- 100% European design, quality and manufacturing

Main features

- Great shielding (class A), made of Zamak
- F connectors with a longer threaded length, to facilitate and secure the installation on a rack plate
- Indoors installation
- Ground screw included
- Does not have any pass outputs

Technical specifications : Ref. 519341

Frequency range	MHz	5 ... 2400	
Number of outputs		4	
Floors		1	
Inputs/Bands		TERR	SAT
Tap losses	dB	8.5	9
Rejection between taps	dB	> 20	> 20
Connectors		"F" female	