



End Outlet 2 connectors: FM-TV

End outlet equipped with two IEC connectors. The left connector is a male IEC for terrestrial TV, the right connector is a female IEC for radio (FM).

| | |
|--------------|---------------|
| Ref. | 5230 |
| EAN13 | 8424450052303 |

Other features

| | |
|-------------------|--------|
| Complement | Outlet |
|-------------------|--------|

Packaging info

| | |
|---------------|-----------|
| Box | 1 pcs. |
| Carton | 10 pcs. |
| Pallet | 3600 pcs. |

Physical data

| | |
|----------------------------|----------|
| Net weight | 90.00 g |
| Gross weight | 90.00 g |
| Width | 70.00 mm |
| Height | 70.00 mm |
| Depth | 27.00 mm |
| Main product weight | 90.00 g |

Highlights

- Robot-controlled automated manufacturing
- High shielding
- Outstanding isolation between outputs

Main features

- Made of Zamak, high strength
- Compatible with coaxial cable with sheath diameters in the 5-to-6,9 mm range (Ø 5...6,9 mm)

Discover

Televes outlets: Screw-free mounting

A class A outlet offering numerous advantages:

- The inner conductor is connected simply by pushing, without the need for screws; still the gripping force is equivalent
- Supports inner conductor diameters from 0.65 mm to 1.2 mm, and external cable diameters from 5 mm to 6.9 mm
- F-connector type conic guide for easy inner conductor introduction
- Wide margin in inner conductor length (from 5 mm to 15 mm), which makes short circuits between core and mesh difficult
- Tilt-up, self-supporting, full-opening clamp
- The clamp is equipped with 3 jagged rows in 9 mm for a perfect braid fixing
- Printed circuit board perforation to make the faceplate fixing screw compatible
- Rounded edges to prevent cuts
- Class A shielding

Furthermore, this product range includes several engravings on the chassis:

- CE marking
- Numerical and logical references
- Input and output indications
- Cable stripping dimensions

Technical specifications : Ref. 5230

| | | | | |
|---------------------------|-----|--------------|----------------|-----------|
| Fastening method | | | Without screws | |
| Number of connectors | | | 2 | |
| R Connector | | | "IEC" female | |
| TV Connector | | | "IEC" male | |
| Pass-through output | | | No | |
| Bands | | | | |
| Frequency range | MHz | FM | | TV |
| | | 87.5 ... 108 | | 5 ... 862 |
| Attenuation: R Connector | dB | 22,5 | | -- |
| Attenuation: TV Connector | dB | -- | | 4,5 |