



5 inputs: FM- HighVHF-14..29-34..51- UHF

High-power multiband amplifier with multiple controls on the front end, which design uses components that minimize the total noise figure. Equipped with 5 inputs (FM-HighVHF-14...34-36...51-UHF). The UHF band is divided in 2 of the inputs, which is useful in two-repeater reception installations since it allows an appropriate filtering of the channels for each of them.

Ref.	534121
EAN13	8424450214565

Packing

Box	1 pcs.
-----	--------

Physical data

Net weight	1,835.00 g
Gross weight	2,150.00 g
Width	280.00 mm
Height	142.00 mm
Depth	48.00 mm
Main product weight	1,834.00 g

Highlights

- Separate amplification minimizes intermodulation between bands and provides high output levels

- Designed using Push-Pull technology, which guarantees levels in the 63 dBmV range for terrestrial signals.
- Includes a high-performance low-power consumption switch-mode power supply
- High-screening Zamak chassis The design facilitates appropriate cooling

Technical specifications

Bands			UHF	BV	BIV	HighVHF	FM
Frequency margin		MHz	470 ... 694	590 ... 698 (Ch34...51)	470 ... 566 (Ch14...29)	174 ... 370	88 ... 108
Gain	0	dB	42	41 ⁽¹⁾	41 ⁽²⁾	42	25
	10		32	31 ⁽¹⁾	31 ⁽²⁾	32	25
Gain margin			(Manual) 0 ... 20	(Manual) 0 ... 20	(Manual) 0 ... 20	(Manual) 0 ... 20	(Manual) 0 ... 20
Max. output level	IMD3 (2 tones,-35 dB)	dBmV	65				
	DIN 45004B		63				
	IMD3 (2 tones,-60 dB)		60				
	IMD2 (2 tones,-60 dB)		-	-	-	62	-
Noise figure		dB	10	10	10	5	6
Test			-20				
Powering inputs		V=	12				
Max. current inputs		mA	50				
Mains voltage /frequency		V~ / Hz	120 ... 230 / 50-60				
Total AC consumption	OFF	W / mA	5,8 / 120				
	ON	W / mA	9,6 / 180				
Protection level		IP	20				
Operating temperature range		°F	23 ... 113				

(1) G(Ch36)=37/27dB

(2) G(Ch34)=38/28dB