



## F 4W splitter with UAP 5...2400MHz 9/8dB

4-way splitter with UAP and F connectors, for SMATV signals. It presents low through losses thanks to the miniaturization applied to the electronic components, which improves its electrical behavior. In addition, its Zamak chassis provides great shielding.

The UAP (User Access Point) provides an additional input for the second downcomer, as specified by ICT-2 regulation concerning installations.

It is conceived for indoor installation, for wall, rack plate or standard DIN rail assembly. Supplied in 10-unit boxes.

<b>Ref.</b>	519534
<b>EAN13</b>	8424450268063

### Packaging info

<b>Box</b>	10 pcs.
------------	---------

### Physical data

<b>Net weight</b>	86.00 g
<b>Gross weight</b>	90.00 g
<b>Width</b>	109.00 mm
<b>Height</b>	54.00 mm
<b>Depth</b>	18.00 mm
<b>Main product weight</b>	86.00 g

## Highlights

---

- Assembly flexibility: it can be installed screwed to the wall, on rack plates with nuts on their connectors, or on a standard DIN rail (with adapter ref. 519901)
- Comfortable screwing of the cable, thanks to a 10° inclination angle of the F-connectors from the installation wall
- Space optimization in registers and cabinets: their inputs/outputs are always located on the same side
- Better organization of the installation: allows cabling passage through its rear part
- F-Series elements can be chained between them with the ground screw, requiring in this case a single grounding cable
- Signal level is maintained in outlets, even with long cable deployment, thanks to a better flatness response
- Outstanding reliability: robotized manufacturing using new generation micro-components
- 100% European design, quality and manufacturing

## Main features

---

- Low through losses
- Great shielding (class A), made of Zamak
- F connectors with a longer threaded length, to facilitate and secure the installation on a rack plate
- Indoors installation
- Ground screw included
- DC pass from the outputs to the input

## Technical specifications : Ref. 519534

Frequency range	MHz	5 ... 2400	
Number of outputs		4	
Inputs/Bands		TERR	SAT
Through losses	dB	9	8
Rejection between outputs	dB	> 20	> 20
Connectors		"F" female	
Voltage max.	V	24	
Max. current	mA	350	
DC pass		OutIn	