



## "F" domestic amplifier 3 outputs (2+TV): VHF/UHF+ Active return channel

Domestic amplifier with 3 outputs (2+TV) to extend the terrestrial television domestic network.

Amplifies the terrestrial band, with active return channel (operator).

The TV output provides a lower gain for direct connection to the television set (no outlet installation).

<b>Ref.</b>	5526
<b>EAN13</b>	8424450055267

### Packaging info

<b>Blister</b>	1 pcs.
<b>Box</b>	8 pcs.
<b>Pallet</b>	640 pcs.

### Physical data

<b>Net weight</b>	280.00 g
<b>Gross weight</b>	280.00 g
<b>Width</b>	146.00 mm
<b>Height</b>	54.00 mm
<b>Depth</b>	35.00 mm
<b>Main product weight</b>	220.00 g

### Highlights

- Low-impact visual design and limited size

- Integrated high-performance switched-mode power supply (40% less than a standard amplifier )
- Fully automated manufacturing subject to the most stringent quality controls

## Main features

---

- Manual gain control, protected by a folding cover
- Can be wall-mounted using screws
- "F" connectors

## Technical specifications : Ref. 5526

<b>Number of outputs</b>			3
<b>TV output</b>			Yes
<b>Frequency range</b>	MHz	5 ... 65	88 ... 862
<b>Gain</b>	dB	9	20
<b>Gain @TV</b>	dB	--	13
<b>Gain adjustment range</b>	dB	--	0 ... 12
<b>Output level DIN45004B</b>	dB $\mu$ V	--	> 107
<b>Noise figure</b>	dB	--	4.5
<b>Input voltage</b>	Vac		207 ... 253
<b>Mains frequency</b>			50 Hz / 60 Hz
<b>Max. current</b>	mA		23
<b>Max. power consumption</b>	W		2.3
<b>Operating temperature</b>	°C		-5 ... 45
<b>Protection index (IP)</b>			20