



End outlet 2 connectors: FM-TV

End outlet equipped with two IEC connectors. The left connector is a male IEC for terrestrial TV, the right connector is a female IEC for radio (FM).

DOCSIS 3.1 compatible.

| | |
|---------------------|---------------|
| Ref. | 523211 |
| Logical ref. | BKE1218-1ST |
| EAN13 | 8424450208533 |

Packing

| | |
|---------------|-----------|
| Box | 1 pcs. |
| Carton | 10 pcs. |
| Pallet | 3600 pcs. |

Physical data

| | |
|---------------------|---------|
| Net weight | 90.00 g |
| Gross weight | 90.00 g |

Highlights

- Robot-controlled automated manufacturing
- High shielding

Main features

- Made of Zamak, high strength
- Compatible with coaxial cable with sheath diameters in the 4.3-to-6,9 mm range (Ø 4.3...6,9 mm)
- With clamp

Technical specifications : Ref. 523211

| | | | | |
|---------------------------|-----|--------------|----------------|------------|
| Fastening method | | | Without screws | |
| Number of connectors | | | 2 | |
| R Connector | | | "IEC" female | |
| TV Connector | | | "IEC" male | |
| Pass-through output | | | No | |
| Bands | | | | |
| Frequency range | MHz | FM | | TV |
| | | 87.5 ... 108 | | 5 ... 1220 |
| Attenuation: R Connector | dB | 1 | | -- |
| Attenuation: TV Connector | dB | -- | | 1 |
| DC pass | | | TVIn | |
| Max. current | mA | | 500 | |