



## MiniKom F line broadband multiband amplifier 1 input: VHF/UHF

Line multiband amplifier (1 input/1 output) for MATV systems. Separate amplification guarantees the absence of intermodulation among inputs and independent attenuators per band (47 MHz- 454 MHz/ 470 MHz - 862 MHz).

<b>Ref.</b>	537302
<b>Logical ref.</b>	MVN137
<b>EAN13</b>	8424450144183

### Other features

**Plug type** EU plug

### Packaging info

**Box** 1 pcs.

**Bucket** 33 pcs.

### Physical data

**Net weight** 1,020.00 g

**Gross weight** 1,020.00 g

**Width** 185.00 mm

**Height** 114.00 mm

**Depth** 64.00 mm

**Main product weight** 960.00 g

### Highlights

- Separate amplification enhance the output level without causing any interference among bands
- PIN-diode technology gain attenuators on each input (0 dB-20 dB)

- Switched configurable gain (high/low), and high output level
- High-screening Zamak chassis

## Main features

---

- "F" connectors
- Output signal LED indicator
- Test output (-30 dB)
- Switch for pre-amplifier or BOSS system powering
- Can be wall-mounted using screws

## Application example

---

