



MiniKom F line broadband multiband amplifier 1 input: VHF/UHF

Line multiband amplifier (1 input/1 output) for MATV systems. Separate amplification guarantees the absence of intermodulation among inputs and independent attenuators per band (47 MHz- 454 MHz/ 470 MHz - 862 MHz).

Ref.	537310
EAN13	8424450178911

Other features

Plug type	US plug
-----------	---------

Packaging info

Box	1 pcs.
-----	--------

Physical data

Net weight	1,100.00 g
Gross weight	1,100.00 g
Width	185.00 mm
Height	114.00 mm
Depth	64.00 mm
Main product weight	828.00 g

Highlights

- Separate amplification enhance the output level without causing any interference among bands
- PIN-diode technology gain attenuators on each input (0 dB-20 dB)
- Switched configurable gain (high/low), and high output level

- High-screening Zamak chassis

Main features

- "F" connectors
- Output signal LED indicator
- Test output (-30 dB)
- Switch for pre-amplifier or BOSS system powering
- Can be wall-mounted using screws

Application example

