



MiniKom F broadband multiband amplifier 4 inputs: FM-BIII-UHF-SAT

4-input multiband amplifier (FM-BIII-UHF-SAT) for SMATV systems. Separate amplification guarantees the absence of intermodulation among inputs and independent attenuators.

Ref.	539620
EAN13	8424450208427

Packaging info

Box	1 pcs.
-----	--------

Physical data

Net weight	888.00 g
Gross weight	1,044.00 g
Width	182.00 mm
Height	117.00 mm
Depth	57.00 mm
Main product weight	888.00 g

Highlights

- Separate amplification enhance the output level without causing any interference among bands
- PIN-diode technology gain attenuators on each input (0 dB-20 dB)
- High output level
- High-screening Zamak chassis

Main features

- “F” connectors
- SAT equalizer
- Output signal LED indicator
- Power selection switch for LNB: local (low-V) or remote
- Switch for pre-amplifier or BOSS system powering
- Test output (-30 dB)
- Can be wall-mounted using screws

Application example

NOTE: To avoid damaging the amplifier, we strongly recommend switching OFF the amplifier until the installation process has been completed.

