



Nemesis V2 Arantia DS Player WiFi

Digital Signage Player with WiFi based on the Nemesis V2 Set-Top Box. Includes a 64 GB microSD memory card for storing the scheduled content through the Arantia DS management tool.

Within the functionalities of this high-definition decoder, the following can be found:

- Support for IPTV and Digital Signage
- Vertical or horizontal image orientation
- Autonomous operation and fail-safe mechanism in the Arantia DS system access network, allowing it to continue playing scheduled content

This device includes the first year of license access to the Arantia DS system for system configurations against the Televes cloud server.

Power supply with EU/UK/US plug included.

Ref.	831831
Logical ref.	ADS-NWV2
EAN13	8424450285947

Packaging info

Box	1 pcs.
------------	--------

Physical data

Net weight	191.00 g
Gross weight	257.00 g

Width	98.00 mm
Height	99.00 mm
Depth	22.00 mm
Main product weight	191.00 g

Highlights

- Allows the establishment of a profitable advertising model, as well as scheduling it in advance for playback at any time
- Displays the last downloaded (scheduled) content during network downtime
- Plays versatile multimedia content, including videos, images, real-time RSS content...
- Horizontal/vertical display
- MPEG2 MPEG4-AVC/H264 platform
- Advanced user interface through the integrated browser
- HDMI interface
- 3x high-speed USB 2.0 ports
- 1x OTG-USB connection
- Interactive TV interface (ITV) and IR extender
- Front panel light indicator
- Includes 2.4/5GHz WiFi antenna
- Built-in Bluetooth
- Remote configuration and monitoring
- Open standard-based software sets
- Flexible open-source-based software
- Standby LED

Technical specifications : Ref. 831831

RAM type		DDR3
RAM	GB	2
Flash Memory capacity	GB	16
Number of Gigabit Ethernet ports (10/100/1000BaseT)		1
USB port		USB 2.0
Number of USB ports		3
Number of OTG ports		1
Number of microSD ports		1
Display port		HDMI
OS		AOSP
Powering	Vdc	5
Max. current	A	2
Max. power consumption	W	5